

CF2QD010C00D –CFP2 Dual Fibre

1310nm* / 10km / 100GBASE – LR4

*1310nm LAN-WDM 800GHz

For your product safety, please read the following information carefully before any manipulation of the transceiver:



ESD

This transceiver is specified as ESD threshold 1kV for SFI pins and 2kV for all others electrical input pins, tested per MIL-STD-883G, Method 3015.4 / JESD22-A114-A (HBM). However, normal ESD precautions are still required during the handling of this module.



LASER SAFETY

This is a Class1 Laser Product according to IEC 60825-1:2007. This product complies with 21 CFR 1040.10 and 1040.11 except for deviations pursuant to Laser Notice No. 50, dated (June 24, 2007).

The optical ports of the module need to be terminated with an optical connector or with a dust plug in order to avoid contamination.

1. Overview

CF2QD010C00D is a high performance CFP2 transceiver module for 100 Gigabit Ethernet data links over a single mode fibre pair. The maximum reach is 10km. The four transmitters are cooled 1310nm LAN-WDM Electro-Absorption Modulated Lasers (EML) or Distributed Feedback (DFB) lasers generating four optical 25Gbps output signals, which are multiplexed together at the optical output port. The four receivers are PIN photodiodes which detect (after optical de-multiplexing) 4× 25Gbps optical input signals.

This transceiver module is compliant with the CFP Multisource Agreement (MSA) and hot pluggable. Always contact Skylane Optics' commercial agents for compatibility with different equipment platforms.

2. Features

- CFP Multi-Source Agreement compliant
- Hot pluggable CFP2 footprint
- Supports 103.125 Gbps Data Rate
- 4× 25.781Gbps Serial Electrical Interface (CEI-28G-VSR)
- Dual LC Optical Connector
- 4× cooled 1310nm LAN-WDM EML/DFB Transmitters
- 4× PIN Receivers
- Up to 10km Point-to-Point Transmission on Single Mode Fibre
- Operating temperature range 0°C to 70°C
- Power Dissipation < 8W
- Single +3.3V Power Supply
- CFP MSA MDIO Management Interface




Figure 1. CFP2 Dual Fibre
(non-binding illustration)

3. Applications

- 100GBASE-LR4

4. Optical Interface

P/N	Wavelength	Protocol	Optical Output Power ¹ [dBm]	Stressed Receiver Sensitivity ² (OMA) [dBm]	Optical Receiver Overload ³ [dBm]	Link Length ^{1,4} [km]
CF2QD010C00D	1310nm LAN-WDM 800GHZ	100GBASE- LR4	1.7 to 10.5	≤ -6.8	4.5	≤ 10

1. EOL over operating temperature range

2. 25.78Gbps, BER≤ 10⁻¹², PRBS 2³¹-1, each lane

3. The optical input to each lane of the receiver should not exceed this value. Transmitters must never be directly connected to receivers before ensuring that proper optical attenuation is used

4. Cabled optical fibre as per IEEE 802.3-2012

5. Technical Parameters

5.1. Recommended Operating Conditions					
Parameter	Min	Typ	Max	Unit	Notes
Storage temperature	-40		85	°C	
Operating Case Temperature	0		70	°C	
Relative Humidity	5		85	%	Non-Condensing
Power Supply Voltage	3.2	3.3	3.4	V	
Power Supply Current			3750	mA	
Power Dissipation			8	W	

5.2. Transmitter Optical Specifications					
Parameter	Min	Typ	Max	Unit	Notes
Data Rate, each Lane		25.78125		Gbps	5
Aggregated Data Rate		103.125		Gbps	5
Average Output Power			10.5	dBm	6
Average Output Power, each Lane	-4.3		4.5	dBm	6,7
Launched OMA, each Lane	-1.3		4.5	dBm	6,8
Launched OMA minus TDP, each lane	-2.3			dBm	6
Difference in launched OMA between any two Lanes			5	dB	
Centre Wavelength, Optical Lanes 0 to 3	1294.53	1295.56	1296.59	nm	
	1299.02	1300.05	1301.09		
	1303.54	1304.58	1305.63		
	1308.09	1309.14	1310.19		
Transmitter and Dispersion Penalty (TDP), each Lane			2.2	dB	
Extinction Ratio, each Lane	4			dB	

5. IEEE 802.3-2012
6. Output power coupled into a 9/125 µm single mode fibre
7. Average launch power, each lane (min) is informative and not the principal indicator of signal strength. A transmitter with launch power below this value cannot be compliant; however, a value above this does not ensure compliance
8. Even if the TDP is <1 dB, the minimum OMA must exceed -1.3dBm

5.3. Receiver Optical Specifications					
Parameter	Min	Typ	Max	Unit	Notes
Operating Wavelength, Optical Lanes 0 to 3	1294.53	1295.56	1296.59	nm	
	1299.02	1300.05	1301.09		
	1303.54	1304.58	1305.63		
	1308.09	1309.14	1310.19		
Average Receive Power, each Lane	-10.6		4.5	dBm	9
Receiver Sensitivity (OMA), each Lane			-8.6	dBm	10
Stressed Receiver Sensitivity (OMA), each Lane			-6.8	dBm	11
Difference in receive power between any two lanes (OMA)			5.5	dB	

9. Average receive power, each lane (min) is informative and not the principal indicator of signal strength. A received power below this value cannot be compliant; however, a value above this does not ensure compliance
10. Receiver sensitivity (OMA), each lane (max) is informative
11. 25.78Gbps, BER_s10⁻¹², PRBS 2³¹-1



6. Transceiver Electrical Pad Layout




Figure 2. Transceiver Electrical Pad Layout

7. Module Electrical Pin Definition

Pin	Symbol	I/O	Description	Logic	Pin	Symbol	I/O	Description	Logic			
1	GND		Ground		53	GND		Ground				
2	TX_MCLKn		Not for normal use		54	NC		Do not connect				
3	TX_MCLKp				55	NC						
4	GND		Ground		56	GND		Ground				
5	NC		Do not connect		57	RX0p	O	Ch0 25Gbps Receive Output	CML			
6	NC				58	RX0n						
7	3.3V_GND		Ground		59	GND		Ground				
8	3.3V_GND				60	RX1p	O	Ch1 25Gbps Receive Output	CML			
9	3.3V	3.3V Power Supply			61	RX1n					Ground	
10	3.3V											
11	3.3V											
12	3.3V											
13	3.3V_GND		Ground		62	GND		Ground				
14	3.3V_GND		Ground		63	NC		Do not connect				
15	VND_IO_A		Do not connect		64	NC						
16	VND_IO_B				65	GND		65	GND		Ground	
17	PRG_CNTL1	I	Programmable Control 1	LVCMOS w/ PUR	66	NC		Do not connect				
18	PRG_CNTL2		67		NC							
19	PRG_CNTL3		68		GND					69	RX2p	O
20	PRG_ALRM1	O	Programmable Alarm 1	LVCMOS	70	RX2n						
21	PRG_ALRM2		71		GND		72	RX3p	O	Ch3 25Gbps Receive Output	CML	
22	PRG_ALRM3		73		RX3n							
23	GND		Ground		74	GND		Ground				
24	TX_DIS	I	Transmitter Disable	LVCMOS w/ PUR	75	NC		Do not connect				
25	RX_LOS	O	Loss of Optical Input Signal	LVCMOS	76	NC						
26	MOD_LOPW	I	Module Low Power Mode	LVCMOS w/ PUR	77	GND		Ground				
27	MOD_ABS	O	Module Absent Indicator	GND	78	REFCLKp		Not Used				
28	MOD_RSTn	I	Module Reset	LVCMOS w/ PDR	79	REFCLKn						
29	GLB_ALRMn	O	Global Alarm	LVCMOS (open drain)	80	GND		Ground				
30	GND		Ground		81	NC		Do not connect				
31	MDC	I	Management Data Clock	1.2V CMOS	82	NC						
32	MDIO	I/O	Management bi-dir. Data	1.2V CMOS	83	GND		Ground				
33	PRTADR0	I	MDIO Physical Port addr. bit0	1.2V CMOS	84	TX0p	I	Ch0 25Gbps Transmit Input	CML			
34	PRTADR1		85		TX0n							
35	PRTADR2		86		GND		87	TX1p	I	Ch1 25Gbps Transmit Input	CML	
36	VND_IO_C	Do not connect			88	TX1n						
37	VND_IO_D				89	GND		90	NC		Do not connect	
38	VND_IO_E				91	NC						
39	3.3V_GND					Ground		92	GND		Ground	
40	3.3V_GND		Ground		93	NC		Do not connect				
41	3.3V	3.3V Power Supply			94	NC						
42	3.3V				95	GND					96	TX2p
43	3.3V											
44	3.3V											

45	3.3V_GND		Ground		97	TX2n			
46	3.3V_GND		Ground		98	GND		Ground	
47	NC		Do not connect		99	TX3p	I	Ch3 25Gbps Transmit Input	CML
48	NC								
49	GND		Ground		101	GND		Ground	
50	RX_MCLKn		Not for normal use		102	NC		Do not connect	
51	RX_MCLKp								
52	GND		Ground		104	GND		Ground	

8. Register Allocation

The total CFP register space (from 8000h to FFFFh) is logically divided into 8 pages with each page starting at even hex thousand, that is, 8000h, 9000h, A000h, ..., F000h, with each page further divided into 32 tables.

The CFP MSA specifies the starting address of all non-volatile registers (NVR) at 8000h (8 NVR tables in total).

Page A000h is allocated for volatile registers (VR). The CFP MSA specifies four VR tables for module configuration, control, and various DDM related functions.

Start Address (hex)	End Address (hex)	Table Name and Description
0000	7FFF	Reserved for IEEE 802.3 use
8000	807F	CFP NVR 1. Basic ID registers
8080	80FF	CFP NVR 2. Extended ID registers
8100	817F	CFP NVR 3. Network lane specific registers
8180	81FF	CFP NVR 4
8200	83FF	MSA Reserved
8400	847F	Vendor NVR 1. Vendor data registers
8480	84FF	Vendor NVR 2. Vendor data registers
8500	87FF	Reserved by CFP MSA
8800	887F	User NVR 1. User data registers
8880	88FF	User NVR 2. User data registers
8900	8EFF	Reserved by CFP MSA
8F00	8FFF	Reserved for User private use
9000	9FFF	Reserved for vendor private use
A000	A07F	CFP Module VR 1. CFP Module level control and DDM registers
A080	A0FF	MLG VR 1. MLG Management Interface registers
A100	A1FF	Reserved by CFP MSA
A200	A27F	Network Lane VR 1. Network lane specific registers
A280	A2FF	Network Lane VR 2. Network lane specific registers
A300	A37F	Network Lane VR 3. Network Lane n Vendor Specific FAWS Registers
A380	A3FF	Reserved by CFP MSA
A400	A47F	Host Lane VR 1. Host lane specific registers
A480	ABFF	Reserved by CFP MSA
AC00	AFFF	Common Data Block Registers
B000	BFFF	Allocated for OIF MSA-100GLH modules
C000	FFFF	Reserved by CFP MSA

Figure 3. Register of a CFP

9. Ordering Information

Part Number	Description
CF2QD010C00D	CFP2 LR4, 1310nm LAN-WDM, Tx (EML/DFB), Rx (PIN), maximum distance 10km on SMF, 100 Gigabit Ethernet, dual LC connector, 0°C to 70°C, DDM

10. Document Revision Information

Revision	Description
A	Initial release
B	References to optical power budget and average power receiver sensitivity removed

Skylane Optics supplies a broad range of optical transceivers. Our engineers work closely with our customers to find the best solutions for every application. We are committed to provide high quality products and services to our customers.

For questions on this product please contact:
support@skylaneoptics.com

**Beyond
Quality**

**Reliable
Alliance**

**Performing
Smartly**